

Cigarette Lighter

Relay Test

1. Remove the glove box (see [section 20](#)).
2. Disconnect the 4-P connector from the cigarette lighter relay (wire colors of 4-P connector: BLU/GRN, YEL/RED, BRN/YEL, BLK).
3. Check continuity at the relay terminals.
 - There should be continuity between the C and D terminals.
 - There should be continuity between the A and B terminals when power and ground are connected to the C and D terminals.
 - There should be no continuity between the A and B terminals when power is disconnected.

